



15182 Triton Lane
Suite #102
Huntington Beach, CA 92649
Phone: (714) 901-5462 Fax: 901-5472
www.pyramidcomm.com

061011
Bulletin Number

Sales Bulletin

SUBJECT: Converting Wideband SVR-200 to Narrowband

DATE: June 10, 2011

The NBK-200 Narrowband Conversion Kit is now available for both the SVR-200VBW (150-174 MHz Wideband) and the SVR-200UDW (450-470 MHz Wideband). The Narrowband Kits are universal for both UHF and VHF, however not all UHF models can be converted. See details below.

VHF Conversion Details:

1. All VHF SVR-200's Pre-Serial Number 749838 will require the NBK-200 Narrowband Kit to be re-banded.
2. The newer VHF SVR-200's that have been shipping since late July 2009 beginning with Serial Number 749838 are Wide / Narrow Band "Jumper Selectable". They will have a W/N jumper located on the underside of the main board, and will not require the NBK-200. To convert unit to Narrowband, solder jumper to "N" side and replace R90 chip resistor with a value of 18k Ω .

UHF Conversion Details:

1. If the UHF SVR-200 unit(s) were purchased before August 2000 and has a Serial Number pre 546828 they cannot be converted to Narrowband.
2. Units purchased between August 2000 and September 2009 and have a Serial Number greater than 546828 and pre 558653 can be converted via the Narrowband Kit.
3. The newest UHF SVR-200's that have been shipping since mid-September 2009 beginning with Serial Number 558653 are Wide / Narrow Band "Jumper Selectable". They will have a W/N jumper located on the underside of the main board, and will not require the NBK-200. To convert unit to Narrowband, solder jumper to "N" side and replace R90 chip resistor with a value of 18k Ω .

Narrowband Kit:

- Part# NBK-200
- Units can be sent in for Factory Conversion

*Please contact your local Pyramid Representative for Pricing.