Annlication Note						AN #: 513E		
							Page 1 of 1	
PYRAMID MODEL #: 2012 / 3012 / 2017 Merlin / 2016ARADIO MODEL: Kenwood TK-x80 Series Mobile V1 & V2EIENGINEER: C. CarbajalD						PPROVAL NGINEER PEPT. HEAD	INITIALS	
Order the Pyramid 2012 TK-x80 interface cable Part # 7514-10-1044 Order the Pyramid 2017/3012 TK-x80 interface cable Part # 7524-10-1044								
Order the Pyramid 2016 TK-x80 interface cable Part # 7534-10-1044								
Connections:	Pyran Dla ala	nid	<i>Function</i>		Radio			
	Black/ White	Shield	Ground Ty Audio Out		KCT-19 Pin 9			
	Rhe		On-AirDetect		KCT-19 Pin 5			
	Green		PTTOut		KCT-19 Pi	KCT-19 Pin 8		
	Red		Switched B+ k		KCT-19 Pi	in 7		
	Yellov	V	Rx Audio In		KCT-19 Pin 4			
	Violet		COR		KCT-19 Pin 11			
(Optional)	(Optional) Brown		Audio Mute Out		N/C			
(Version 2 Only)	(Version 2 Only) Grey		Mic Mute/Channel Select		KCT-19 Pi	in 15		
2012/Merlin J1 Jumpers: J2	[Out] [Out]	TX audio le PTT loop b	evel back	Pyramid Program:	Mobile COR Mobile Type	R Polarity: e: rity:	High Conv/Trunk High	
2016 J1 Jumpers: J2	[Out] [Out]	PTT loop b TX audio le	back evel		I/O Pin 9	inty.	Mute	
Additional Modifications (Pyramid): None								
Additional Modifications (Radio): Install the KCT-19 "E" plug into CN-2.								
Using the KPG-49 software, program the following:								
1. Program the COR output for active high under the <i>Edit/Optional Features/Logic Signalling</i> ; Select "Squelch Logic Type: High" and "Squelch Logic Signal : TOR".								
2. To enable PTT input on pin 8 of the KCT-19, under Edit/Optional Features, program Com2 as "Aux Hook/PTT".								
<i>Note for Version 1 Radios:</i> To enable Data Terminal Channel select on the TK-x80 series Version 1 radios, you must use Kenwood 80 series firmware version 8050 checksum. Additionally you will need to designate one talk group per system as data. To do this, select the talk group and hit F9 (Set System/Group #). Also, select data talk group again, and hit F10 (Set Data=YES). A detailed installation guide is available, contact Pyramid Technical Support.								
<i>Note for Version 2 Radios:</i> To enable Data Terminal Channel select on the TK-x80 series Version 2 radios, you must connect the Grey wire from the Pyrmaid to Pin 15 of the KCT-19. Additionally you will need to designate one talk group per system as data. To do this, select the talk group and hit F9 (Set System/Group#). Also, select data talk group again, and hit F10 (Set Data=YES). A detailed installation guide is available, contact Pyramid Technical Support.								